

C Suite Digitizing

Using DVCAM Tape:

Use the Sony DSR-30 machine (next to the computer).

1) Turn on Machine.

2) Using the Sony DSR-30 Deck press the "Input select" button to read "DV In" on the machine's display. (your choices are L1, L2, DV In)

3) Make sure "External Video" (found under the "View" menu) within the FCP program is set to "All Frames".

4) Go to "Log and Capture" under the "File" menu. Set your scratch discs to your folder.

Using DVCPRO Tape:

You must first unplug the Sony DSR-30 videotape deck. You can not have two tape machines plugged in at the same time. The computer will lock up.

1) Plug in black Firewire cable marked "C-suite to Firewire router".

2) In order to hear audio while digitizing you need to patch both video and audio to C suite from DVCPRO. Using the patch cables patch in the following way:

Video Output: Plug video patch cable into "DVCPRO deck out" (yellow dot).

Video Input: Under the heading "video from DV converter(s) in "C" suite. Plug other end of video patch cable into "DV CNV #1 in".

Audio Output: Plug two audio patch cable (left and right) into "Kramer Router – DA – RDL out" (Orange dot)

Audio Input: Plug other end of audio patch cables into the upper set of audio inputs (right under monitor) into "C suite DV CNV #1 Input".

On the Kramer Router press the "DVC Pro" button (gray and blue).

Turn on the nine inch JVC monitor – you will be getting your audio from this TV set and through the external speakers.

On the DSR-30 Deck press the "Input select" button to read "DV In" on the machine's display. (your choices are L1, L2, DV In)

Make sure "External Video" (found under the "View" menu) within the FCP program is set to "All Frames".

Set up your scratch disc to your file, using the scratch disc tab in the digitizing window.

Make sure DVC Pro Deck is set to your tape format:

Using the Menu switch, go to operation: scroll down to 107 "Format Select", then select DVCPRO and press enter (the red record button)